

LM-Series With Monitor
L-Series With Out Monitor

MTW-Series
MST-Series
MT-Series



ALL SPECIFICATIONS LM / L-Series

Series	Input voltage (volt) at Impedance (Ohms)		Output Impedance (Ohms) at Voltage (Volt)		Input fuse (Amp) at Impedance (Ohms)	
	L	LM				
	4	8	70	100	4	8
120	21.90	30.90	49.00	100.00	7.75	5.48
200	28.20	40.00	32.50	67.00	10.00	7.07
300	34.60	48.90	24.50	50.00	12.25	8.66
400	40.00	56.50	16.00	33.00	14.14	10.00
500	44.70	63.20	12.00	25.00	15.81	11.18
600	48.90	69.20	10.00	20.00	17.32	12.25
700	52.90	74.83	8.00	16.50	18.71	13.23
800	56.57	80.00	7.00	14.00	20.00	14.14
900	60.00	84.85	6.00	12.50	21.21	15.00
1000	63.25	89.40	5.50	11.00	22.36	15.81
1200	69.20	97.90	5.00	10.00	24.49	17.32

ALL SPECIFICATIONS AUDIO LINE TRANSFORMER FOR SPEAKERS

For Music Speaker	Model	Input Voltage	Output Impedance	Power
	MT-5M	70/100V	4/8Ω	1.25/2.5/5 Watts
	MT-10M	70/100V	4/8Ω	2.5/5/10 Watts
	MT-25M	70/100V	4/8Ω	3.1/6.25/12.5/25 Watts
	MT-50M	70/100V	4/8Ω	3.1/6.25/12.5/25.50 Watts
	MST-5M	70/100V	8Ω	1/2/3/5 Watts
	MST-10M	70/100V	8Ω	3/5/7/10 Watts
For Horn Speaker	MT-25H	70/100V	8/16Ω	6.25/12.5/25 Watts
	MT-45H	70/100V	8/16Ω	6.12/12/22.5/45 Watts
	MT-100H	70/100V	8/16Ω	12.5/25/50/100 Watts
For Water proof Horn Speaker	MTW-45	50/70/100V	8/16Ω	45 Watts
	MTW-100	50/70/100V	8/16Ω	100 Watts

Note: Specifications and design subject to modification without notice.



Natthapong Sales & Service Co., Ltd.

119 Assadang Rd. Wang Burapaphrom Pranakorn
Bangkok 10200, Thailand
Tel : 225-0094 (8 Line Auto)
Fax : 226-4020 (local), 225-2528 (intl) E-Mail: NPE@IBM.NET