

MPR-SERIES

Multiple Power Outlet Rack



MPR-SERIES

Multiple Power Outlet Rack



MPR 208VA



| BACK |

SPECIFICATION	MPR-208VA
Model :	MPR-208VA
Max current :	Breaker1 , Breaker2: 30Ax2
Power Frequency :	50Hz or 60Hz
Power Input :	AC 220V 50/60Hz
Channels :	8 channels(4 CH x 2)
Display :	AC Digital Voltage meter & AC Digital Current meter
Voltage Meter :	Digital Voltage meter display, +/-1% no-load accuracy, +/-1% accuracy of full-load
Current Meter :	Digital Current meter display, +/-1% no-load accuracy, +/-1% accuracy of full-load
Alarm :	It Alarm when overvoltage is out of range which you setup (Voltage more 260Vac 50/60Hz)
Dimension :	483 X 210 X 88 mm
Net Weight :	6.00 kg



MPR 108VA



| BACK |

SPECIFICATION	MPR-108VA
Model	MPR-108VA
Max current	Breaker 1: 30A
Power Frequency	50Hz or 60Hz
Power Input	AC 220V 50/60Hz
Channels	8 Channels
Display	AC Digital Voltage meter & AC Digital Current meter
Voltage Meter	Digital Voltage meter display, +/- 1% no-load accuracy, +/- 1% Accuracy of full-load
Current Meter	Digital Voltage meter display, +/- 1% no-load accuracy, +/- 1% Accuracy of full-load
Alarm	It alarms when overvoltage is out range which you setup (Voltage more 250Vac 50/60Hz)
Dimensions : (WxHxD) Net/Shipping	483x88x210mm / 525x175x393mm
Weight : Net/Shipping	6.30kg(13.889lbs)



MPR 208VAU



| BACK |

SPECIFICATION	MPR-208VAU
Model	MPR-208VAU
Max current	Breaker 2: 30A x 2
Power Frequency	50Hz or 60Hz
Power Input	AC 220V 50/60Hz
Channels	8 Channels (4CH. x 2)
Display	AC Digital Voltage meter & AC Digital Current meter
Voltage Meter	Digital Voltage meter display, +/- 1% no-load accuracy, +/- 1% Accuracy of full-load
Current Meter	Digital Voltage meter display, +/- 1% no-load accuracy, +/- 1% Accuracy of full-load
Alarm	It alarms when overvoltage is out range which you setup (Voltage more 250Vac 50/60Hz)
Dimension : (WxHxD) Net/Shipping	483x88x210mm / 525x175x393mm
Weight : Net/Shipping	6.30kg(13.889lbs)



MPR 108VAU



| BACK |

SPECIFICATION	MPR-108VAU
Model	MPR-108VAU
Max current	Breaker 1: 30A
Power Frequency	50Hz or 60Hz
Power Input	AC 220V 50/60Hz
Channels	8 Channels
Display	AC Digital Voltage meter & AC Digital Current meter
Voltage Meter	Digital Voltage meter display, +/- 1% no-load accuracy, +/- 1% Accuracy of full-load
Current Meter	Digital Voltage meter display, +/- 1% no-load accuracy, +/- 1% Accuracy of full-load
Alarm	It alarms when overvoltage is out range which you setup (Voltage more 250Vac 50/60Hz)
Dimensions : (WxHxD) Net/Shipping	483x88x210mm / 525x175x393mm
Weight : Net/Shipping	6.30kg(13.889lbs)



MPR 208U



| BACK |

SPECIFICATION	MPR-208U
Model	MPR-208U
Max current	Breaker 1, Breaker2 : 30Ax2
Power Frequency	50Hz or 60Hz
Power Input	AC 220V 50/60Hz
Channels	8 Channels (4CH.x2)
Dimensions : (WxHxD) Net/Shipping	483x88x210mm / 525x175x393mm
Weight : Net/Shipping	6.30kg(13.889lbs)



MPR 108U



| BACK |

SPECIFICATION	MPR-108U
Model	MPR-108U
Max current	Breaker 1: 30A
Power Frequency	50Hz or 60Hz
Power Input	AC 220V 50/60Hz
Channels	8 Channels
Dimensions : (WxHxD) Net/Shipping	483x88x210mm / 525x175x393mm
Weight : Net/Shipping	6.30kg(13.889lbs)

All features & specifications subject to change without notice. © NPE Industry (Thailand) Co., Ltd June 2012
Distributor :

บริษัท นัทพงษ์ เซลส์แอนด์เซอร์วิส จำกัด
Natthapong Sales & Service Co., Ltd.
สำนักงานใหญ่ : 119,119/1 ถนนอภัยวงศ์ แขวงพญาภิรมย์ พระนคร กรุงเทพฯ 10200
โทรศัพท์ : 0-2225-0094, 0-2623-8899 (อัตโนมัติ 18 เลขหมาย) โทรสาร : 0-2226-4020
สาขาเชียงใหม่ : ชั้น 6 (ด้านในสุด) 99 หมู่ 8 ถนนพหลโยธิน ดุสิต อ.ลำลูกกา ร.พญาธานี 12130 โทรศัพท์ : 0-2992-7379 โทรสาร : 0-2992-7380
www.mynpe.com : www.facebook.com/mynpethailand
E-Mail : mynpe@mynpe.com

Note : 0dBu = 0.775Vrms, 0dBV = 1Vrms
www.mynpe.com
E-Mail : mynpe@mynpe.com

