

# ZMR SERIES

## ZMX 862

6-Channel 2 Mono 2 Stereo Compact Mixer



## ZMX 122 FX

8-Channel 4 Mono 2 Stereo Compact Mixer With Effects



## ZMX 52

5-Channel 1 Mono 2 Stereo Compact Mixer



## ZMX 122 FX

8-Channel 4 Mono 2 Stereo Compact Mixer with Effects

### TECHNICAL SPECIFICATIONS

<b>IMPEDANCE</b>	
Mic inputs	3.9 k $\Omega$
All other inputs	$\geq 10$ k $\Omega$
Aux output	1 k $\Omega$
All outputs	120 $\Omega$
<b>EQUALIZATION</b>	
High	$\pm 15$ dB @ 12 kHz
Mid	$\pm 15$ dB @ 2.5 kHz
Low	$\pm 15$ dB @ 80 Hz
<b>DSP</b>	
A/D and D/A converters	24-bit
DSP Resolution	24-bit
Effects	Reverbs: Hall, Room, Vocal, Plate Delays: Mono, Stereo (max delay time: 650 ms) Modulations: Chorus, Flanger, Reverb Combinations: Reverb + Delay, Reverb + Chorus, Reverb + Flanger
Presets	256
Controls	256-position preset selector, clip LED, mute switch, foot switch, LED
<b>POWER SUPPLY</b>	18 V, 1000mA
<b>POWER CONSUMPTION</b>	18 W
<b>DIMENSIONS (W x D x H)</b>	10.1" x 9.8" x 2.9" (256 mm x 250 mm x 72 mm)
<b>WEIGHT</b>	5.1 lbs (2.3 Kg)

## ZMX 52

5-Channel 1 Mono 2 Stereo Compact Mixer

## ZMX 862

6-Channel 2 Mono 2 Stereo Compact Mixer

### TECHNICAL SPECIFICATIONS

<b>IMPEDANCE:</b>	
Mic inputs	3.9 k $\Omega$
All other inputs	$\geq 10$ k $\Omega$
Aux outputs	1 k $\Omega$
All outputs	120 $\Omega$
<b>EQUALIZATION</b>	
ZMX 52	
High	$\pm 15$ dB @ 12 kHz
Low	$\pm 15$ dB @ 80 Hz
ZMX 862	
High	$\pm 15$ dB @ 12 kHz
Mid	$\pm 15$ dB @ 2.5 kHz
Low	$\pm 15$ dB @ 80 Hz
<b>POWER SUPPLY</b>	
ZMX 52	18 V, 500 mA
ZMX 862	18 V, 1000 mA
<b>POWER CONSUMPTION:</b>	
ZMX 52	9 W
ZMX 862	18 W
<b>DIMENSIONS (W x D x H):</b>	
ZMX 52	5.1" x 8" x 1.5" (128 mm x 204 mm x 38 mm)
ZMX 862	8" x 9.8" x 2.3" (202 mm x 250 mm x 58 mm)
<b>WEIGHT:</b>	
ZMX 52	1.65 lbs (0.75 kg)
ZMX 862	3.8 lbs (1.7 kg)