



ACT-24HC
Digital Handheld Transmitter

ACT-24TC
Digital Bodypack Transmitter

ACT-2412A

Detachable Antenna Dual-Channel Digital Receiver

SPECIFICATIONS

RECEIVER		TRANSMITTER	
MODEL	ACT-2412A	MODEL	ACT-24HC ACT-24TC
CHANNEL	Dual - Channel	FREQUENCY RANGE	2.402 - 2.482 GHz
FREQUENCY RANGE	2.402 - 2.482 GHz	CHANNEL SET UP	ACT Sync
ANTENNA	Detachable Antenna x 2	RF OUTPUT POWER	2 mW/10 mW Switchable (Country Dependent)
RECEIVING MODE	Dual - Tuner Digital Diversity	TRANSMITTER MODE	Frequency Hopping
SENSITIVITY	-95 dBm	MAX AUDIO INPUT	6.5 dBV
FREQUENCY RESPONSE	20 Hz ~ 20 KHz (-2 dB)	BATTERY METER	4 - Level Green / Red LED Display
DISPLAY	Graphic OLED	BATTERY TYPE	ICR 18500 Rechargeable Lithium Battery X1
AUDIO OUTPUT	3 Option: +20 dBV / 0 dBV / -10 dBV	CURRENT CONSUMPTION	Approx 138 mA
OUTPUT CONNECTORS	Balanced XLR & Jack TRS Phone	DIMENSIONS	(ØxL) 50 x 248 mm. (WxHxD) 63 x 70 x 25 mm.
POWER SUPPLY	External AC Power Supply	WEIGHT	Approx 225 g / 3.1 oz Approx 62 g / 2.2 oz
DIMENSION (WxHxD)	420 x 44 x 180 mm. / 16.5 x 1.7 x 7.1"		
WEIGHT (kg/lbs)	Approx 1.4 kg / 3.1 lbs		

JULY 2018

All features & specifications subject to change without notice. © Natthapong Sales & Service Co.,Ltd.

สนใจสามารถสอบถามสินค้าจากตัวแทนจำหน่ายทั่วประเทศ

Distributor :

@ mynpethailand



บริษัท นัฐพงษ์ เซลส์แอนด์เซอร์วิส จำกัด
Natthapong Sales & Service Co.,Ltd.
www.mynpe.com : E-Mail : mynpe@mynpe.com



สำนักงานใหญ่ : 119,119/1 ถนนอภัยวงศ์ แขวงพญาภิรมย์ พระนคร กรุงเทพฯ 10200
โทรศัพท์ : 0-2225-0094,0-2623-8899 (อัตโนมัติ 18 เลขหมาย) โทรสาร : 0-2226-4020
สาขาเซียร์รังสิต : ชั้น G (ด้านในสุด) 99 หมู่ 8 ถนนพหลโยธิน ต.คูคต อ.ลำลูกกา จ.ปทุมธานี 12130 โทรศัพท์ : 0-2992-7379 (อัตโนมัติ 10 เลขหมาย) โทรสาร : 0-2992-7380
สาขาศาลายา : 9/8 หมู่ 2 ต.บางเตย อ.สามพราน จ.นครปฐม 73210
โทรศัพท์ : 0-2889-5496-8