

LM-Series With Monitor
L-Series With Out Monitor

MTW-Series
MST-Series
MT-Series



ALL SPECIFICATIONS LM / L-Series

Series		Input voltage (volt) at Impedance (Ohms)		Output Impedance (Ohms) at Voltage (Volt)		Input fuse (Amp) at Impedance (Ohms)	
		L	LM				
		4	8	70	100	4	8
120		21.90	30.90	49.00	100.00	7.75	5.48
200		28.20	40.00	32.50	67.00	10.00	7.07
300		34.60	48.90	24.50	50.00	12.25	8.66
400		40.00	56.50	16.00	33.00	14.14	10.00
500		44.70	63.20	12.00	25.00	15.81	11.18
600		48.90	69.20	10.00	20.00	17.32	12.25
700		52.90	74.83	8.00	16.50	18.71	13.23
800		56.57	80.00	7.00	14.00	20.00	14.14
900		60.00	84.85	6.00	12.50	21.21	15.00
1000		63.25	89.40	5.50	11.00	22.36	15.81
1200		69.20	97.90	5.00	10.00	24.49	17.32

ALL SPECIFICATIONS AUDIO LINE TRANSFORMER FOR SPEAKERS

For Music Speaker.....	Model.	Input Voltage	Output Impedance	Power
	MT-5M.....	70/100V.....	4/8Ω.....	1.25/2.5/5 Watts
	MT-10M.....	70/100V.....	4/8Ω.....	2.5/5/10 Watts
	MT-25M.....	70/100V.....	4/8Ω.....	3.1/6.25/12.5/25 Watts
	MT-50M.....	70/100V.....	4/8Ω.....	3.1/6.25/12.5/25.50 Watts
	MST-5M.....	70/100V.....	8Ω.....	1/2/3/5 Watts
	MST-10M.....	70/100V.....	8Ω.....	3/5/7/10 Watts
For Horn Speaker.....	MT-25H.....	70/100V.....	8/16Ω.....	6.25/12.5/25 Watts
	MT-45H.....	70/100V.....	8/16Ω.....	6.12/12/22.5/45 Watts
	MT-100H.....	70/100V.....	8/16Ω.....	12.5/25/50/100 Watts
For Water proof Horn Speaker.....	MTW-45.....	50/70/100V.....	8/16Ω.....	45 Watts
	MTW-100.....	50/70/100V.....	8/16Ω.....	100 Watts

Note: Specifications and design subject to modification without notice.



myNPE.com



Natthapong Sales & Service Co., Ltd.

119, 119/1 Assadang Rd. Wangburapapirhom Pranakorn
Bangkok 10200, Thailand.
Tel : 0-2225-0094, 0-2623-8899 (18 Line Auto.)
Fax : 0-2226-4020 (local), 0-2225-2528 (int'l)
E-Mail : npe@npe.co.th Web site: <http://www.mynpe.com>
<http://www.npe.co.th>