

KSA-MP3 SERIES



SPECIFICATIONS	KSA-300MP3	KSA-500MP3
Connectors	2 Binding Posts	
Power Output	150 W / 8Ω 250 W / 4Ω	250 W / 8Ω 450 W / 4Ω
Mic Input:	Balanced / 1/4" TRS	
Type / Connectors		
Input Impedance	2.2 kΩ	
Input Sensitivity @8Ω	-52 dBu	
Frequency Response @0, -3 dB	20 Hz - 20 kHz	
Hum & Noise	< -30 dBu	
THD+N @1 kHz	0.1 %	
Maximum Level	-30 dBu	
Aux Input:	Unbalanced / RCA	
Type / Connectors		
Input Impedance	47 kΩ	
Input Sensitivity @8Ω	-15 dBu	
Frequency Response @0, -2 dB	20 Hz - 20 kHz	
Hum & Noise	< -35 dBu	
THD+N @1 kHz	0.1 %	
Maximum Level	10 dBu	
Subwoofer Out:	Unbalanced / RCA	
Type / Connectors		
Frequency Response	60 Hz - 380 Hz	
Shift Phase	0° - 180°	
Mic Tone Control:	3 Stage Bass, Mid and High	
Low	±12 dB @60 Hz Shelving	
Mid	±12 dB @1 kHz Peaking	
High	±12 dB @12 kHz Shelving	
Line Tone Control:	3 Stage Bass, Mid and High	
Low	±12 dB @80 Hz Shelving	
Mid	±12 dB @1 kHz Peaking	
High	±12 dB @12 kHz Shelving	
Echo Delay Time Control:	150 - 450 ms	
FM Tuner Frequency:	87.5 MHz - 108 MHz	
Power Requirement:	220 VAC 50 Hz	
Power Consumption: Idle / Rate 4Ω	34 W / 945 W	70 W / 1,580 W
Dimensions: (WxHxD)	435 x 132 x 460 mm	
Net Weight:	17.4kg (38.28 lbs)	19.4 kg (42.68 lbs)

FEATURES

- เป็นเครื่องขยายเสียงสเตอริโอคาราโอเกะ
- KSA-300MP3 กำลังขยาย 150W+150W ที่ 8 โอห์ม 250W+250W ที่ 4 โอห์ม
- KSA-500MP3 กำลังขยาย 250W+250W ที่ 8 โอห์ม 450W+450W ที่ 4 โอห์ม
- มีชุดปรับแต่งเสียง ทุ้ม-กลาง-แหลม
- มีเครื่องเล่น USB/SDHC/MP3/FM Radio/Bluetooth
- มี Digital Echo และระบบตัดเสียงร้องอัตโนมัติ เมื่อพูดไมค์
- มีช่องต่อ Subwoofer Out สามารถปรับความถี่และเฟสได้
- มีจุดเชื่อมต่อตู้ลำโพง 2 คู่
- มีระบบป้องกันลำโพงด้วยวงจรจอร์จอีลิกทรอปิกส์ (DC-Protection, On-Delay Timer)

SYSTEM DIAGRAM



Note: 0dBu=0.775Vrms, 0dBV=1Vrms

All features & specifications subject to change without notice. © NPE Industry (Thailand) Co., Ltd. (R1) 19 September 2023

Distributor :

บริษัท นัทพงษ์ เซลส์แอนด์เซอร์วิส จำกัด
Natthapong Sales & Service Co., Ltd.

สำนักงานใหญ่ : 119,119/1 ถนนอภัยวงศ์ แขวงบูรพาภิรมย์ พระนคร กรุงเทพฯ 10200
 โทรศัพท์ : 0-2225-0094, 0-2623-8899 (อัตโนมัติ 18 เลขหมาย) โทรสาร : 0-2226-4020

สาขาเชียงใหม่ : ชั้น G (ด้านในสุด) 99 หมู่ 8 ถนนพหลโยธิน ต.สุคนธ์ อ.ลำลูกกา จ.ปทุมธานี 12130
 โทรศัพท์ : 0-2992-7379 โทรสาร : 0-2992-7380

สาขาศาขลา : 9/8 หมู่ 2 ถนนบางกอกน้อย-นครชัยศรี ต.บางเตย อ.สามพราน จ.นครปฐม 73210
 โทรศัพท์ : 0-2889-5496-8 โทรสาร : 0-2889-5866

E-Mail : mynpe@mynpe.com www.mynpe.com



@mynpethailand

