

PBM-602

Stereo Powered Mixer 2x250W

FEATURE

- 10 Channel Power Mixer (6/8 Mono, 2 Stereo Input)
- 3 Band EQ on All Inputs
- 1 Aux Send for External Effects and Monitoring
- Peak LED on All Inputs
- 32 BIT 16 DSP Digital Effects
- USB, MP3, Record, Bluetooth
- Dual 7 Band Graphic EQ for Main Mix
- +48V Phantom Power Supply



SPECIFICATIONS

MODEL

PBM-602

POWER OUTPUT (Stereo 8 Ohm/CH)

250W x 2

FREQUENCY RESPONSE

25Hz – 18 kHz

T.H.D.

0.1 % @ 1 kHz

SIGNAL TO NOISE RATIO

> 90dB

CHANNEL EQ : HIGH

+/-15dB 12k

: MID HIGH

+/-15dB 2.5k

: LOW

+/-15dB 80Hz

DIMENSION (WxDxH)

440x300x270 mm.

WEIGHT

12 kg.

POWER SUPPLY

AC 220V/60Hz

All features & specifications subject to change without notice. © Natthapong Sales & Service Co.,Ltd.

Distributor :

 บริษัท บัญพงษ์ เซลล์แอนด์เซอร์วิส จำกัด
Natthapong Sales & Service Co.,Ltd.
www.mynpe.com : E-Mail : mynpe@mynpe.com



สำนักงานใหญ่ : 119,119/1 ถนนอภัยวงศ์ แขวงพญาภิรมย์ พระนคร กรุงเทพฯ 10200
โทรศัพท์ : 0-2225-0094, 0-2623-8899 (อัตโนมัติ 18 เลขหมาย) โทรสาร : 0-2226-4020
สาขาเชียงใหม่ : ซีน G (ด้านในสุด) 99 หมู่ 8 ถนนพหลโยธิน ต.สุเกต อ.ลำลูกกา จ.ปทุมธานี 12130
โทรศัพท์ : 0-2992-7379 (อัตโนมัติ 10 เลขหมาย) โทรสาร : 0-2992-7380
สาขาสาลายา : 9/8 หมู่ 2 ต.บางเตย อ.สามพราน จ.นครปฐม 73210
โทรศัพท์ : 0-2889-5496-8

May 2020

สนใจสามารถสอบถามสินค้าจากตัวแทนจำหน่ายทั่วประเทศ

@mynpethailand     